

ТАБЛИЦА ПРИМЕНЕНИЯ ДВИГАТЕЛЕЙ РАЗЛИЧНЫХ МОДЕЛЕЙ					
Двигатель	Левый	Правый	Высота	Ширина	Длина
Серия 0-320					
-A1A, -A1B	S4LN-21	S4LN-20	22,99	32,24	29,56
-A2A*, -A2B*	S4LN-21	S4LN-20	22,99	32,24	29,56
-A3A, -A3B	S4LN-21	S4LN-20	22,99	32,24	29,56
-A2C*, -A3C	S4LN-200	S4LN-204	22,99	32,24	29,81
-B1A, -B1B	S4LN-21	S4LN-20	22,99	32,24	29,56
-B2A*, -B2B*	S4LN-21	S4LN-20	22,99	32,24	29,56
-B3A, -B3B	S4LN-21	S4LN-20	22,99	32,24	29,56
-B2C*, -B3C	S4LN-200	S4LN-204	22,99	32,24	29,81
-D1A, -D2A*	S4LN-21	S4LN-20	22,99	32,24	29,56
-D1B, -D2B*	S4LN-200	S4LN-204	22,99	32,24	29,56
-D1C, -D2C*	S4LN-1227	S4LN-1209	22,99	32,24	30,70
-D1F, -D2F*	S4LN-1227	S4LN-1209	22,99	32,24	30,70
-E1A, -E2A*	S4LN-21	S4LN-20	22,99	32,24	29,56
-E1B, -E2B*	S4LN-200	S4LN-204	22,99	32,24	29,81
-E1C, -E2C*	S4LN-1227	S4LN-1209	22,99	32,24	30,70
-E1F, -E2F*	S4LN-1227	S4LN-1209	22,99	32,24	30,70
-E2D*, -E3D*	4051	4050	22,99	32,24	29,05
-A2D*, -E2G*	4051	4050	22,99	32,24	29,05
-D2G, -D3G	4051	4050	22,99	32,24	29,05
-E2H*, -E3H*	S4LN-21	S4LN-20	22,99	32,24	29,56
-D1D	4051	4050	19,22	32,24	31,82
-D2J*	4251	4251	23,00	32,24	29,05
Серия IO-320					
-A1A, -A2A*	S4LN-200	S4LN-204	19,22	32,24	33,59
-B1A, -B2A*	S4LN-21	S4LN-20	19,22	32,24	33,59
-B1B	S4LN-21	S4LN-20	19,22	32,24	33,59
-B1C	S4LN-21	S4LN-20	19,22	32,24	32,09
-B1D	S4LN-1208	S4LN-1209	19,22	32,24	32,09
-C1A	S4LN-21	S4LN-21	19,22	32,24	33,59
-D1A, -D1B	S4LN-1227	S4LN-1209	23,18	32,24	30,70
-E2B*	4051	4050	23,18	32,24	29,05
-E1A, -E2A*	S4LN-21	S4LN-20	23,18	32,24	29,56

* Пропеллер с фиксированным шагом